



SIVA INSTRUMENTS

Transformer Winding Resistance Meter

Model : TWRM-25A uP



Introduction

Transformer Winding Resistance Meter is designed to measure the winding resistance of transformers, Inductors, generators and motor windings, Tap Changers Etc.

It is specially designed for Highly Inductive objects like 400KV/220KV. Special care is taken for measuring 3 phase transformers by using band switch matrix, to avoid climbing on transformers for safe & measurements. This is only indigenous TWRM which gives very fast readings for 3Phase Star-Delta any combination Transformers. The built in open circuit Voltage of DC Supply ensures that core of the transformer is saturated for fast measurements to be taken. Care is taken to absorb the Back emf of such transformers. For user safety, Indication for discharges is provided on front panel , if the current through winding under measurement is disturbed/discontinued.

Instrument has built in 10A regulated and highly stable current source with current selection of 25 Amp, 10Amp, 1Amp, 0.1Amp & 0.01Amp.

Instrument uses ratio-metric circuit where the resistance of specimen is compared with known internal standard and 4 ½ digit LED/LCD display is provided for resistance measurement in milliohms and in ohms.

Features

- Easy & Fast switching for 3 phase to avoid changing Primary-Secondary, Band switch is provided on front panel.
- Regulated and highly stable 25Amp, 10 Amp, 1Amp, 0.1Amp & 0.01Amp current source.
- 4½ digit LED/LCD display .
- Simultaneous measurements of voltage & current.
- True four terminal measurement.
- Resolution of 0.1 micro ohm
- Protection against inductive kickback and discharge.
- Visual indication for discharge.
- Line voltage interference suppression , making instrument most suitable for field applications.
- Light weight with carrying case & with 10 meter leads.
- Inbuilt Printer, RS232 port , Data acquisition software.

Specifications

POWER SUPPLY	230V AC, 50Hz, single phase.
TEST CURRENT	25 Amp, 10 Amp , 1Amp , 0.1Amp & 0.01Amp
RANGES	0.1u ohm to 200 ohms in 6 Ranges
INDICATION	4 ½ Digital panel meter LED/ LCD (5 Decades i.e.20000 count)
RESOLUTION	0.1 micro ohm on 2 milli ohm range
ACCURACY	0.5% ± 1 digits over the entire range.
OPTIONAL	RS232 Port, Inbuilt printer, Data Acquisition Software
CONTROLS	Power On Switch. Current Range selection switch. Matrix Switching for winding selection.
DIMENSIONS	L=440x B=350x H= 150mm ± 10mm
WEIGHT	Approx. 20Kg

SIVANANDA ELECTRONICS

DEEPAK MAHAL, LAM ROAD, DEVLALI-422 401, NASHIK. MAHARASHTRA, INDIA.

Phone : 0253-2491423, 2491504, 2491816 E-mail : mkb@sivanandaelectronics.com Fax: 0253-2492291

MUMBAI : 208, MIDAS Sahar Plaza Complex, Andheri Kurla Road, Andheri (E) Mumbai 400059.

Ph: 56430590, Fax : 28389232.

NEW DELHI : G -145, KALKAJI, NEW DELHI -110 019. • PHONE : 26221582, 26434442, FAX: 011-26434440

BANGALORE : 44/2, DICKENSON ROAD, BANGALORE - 560 042 • PHONE : 5585673

HYDERABAD : 310, JAMUNA MANSION, CHIRAG ALI LANE, ABIDS, HYDERABAD-500 001. • PHONE : 23202943

MFRS. OF : ELECTRONIC INSTRUMENTS, METAL DETECTORS, TURNSTILES, COMPUTERISED ATTENDANCE RECORDING & ACCESS CONTROL