



SIVA INSTRUMENTS



BREAKDOWN VOLTAGE TESTER

Model : HVO-35 35KV AC 75mA



Special Features

- Metal Cabinet.
- Selectable Trip Current.
- Epoxy Molded Transformer.
- Provided with safety features.
- Portable.
- Easy to Operate.

Technical Specifications

Test Voltage: 0-35KV AC.

Accuracy : $\pm 2\%$ of reading ± 2 digits.

Trip Current : 75 mA Pre-Settable.

Timer : 0-999Seconds

Auto/Manual Modes : In Auto Mode Auto Voltage Setting, Auto Trip Settings & Timer Settings will have control over test. Push Buttons & Knobs are provided for settings.

Dimmerstat : Motorized.

Display : 3 1/2 DPM display for Voltage & Current
3 digit for Timer. Same displays used for Preset Value settings.

Controls : Power ON, HV ON, HV OFF, Reset, Voltage Increase/Decrease, Audio Visual Failure & HV indicator.

Input : 230 VAC , 50Hz , single Phase

Protections : Zero Start Protection

: HV Cover interlock.

Open Ground Protection.

To keep pace with the latest technology Sivananda Electronics reserves the right to update it's system. Hence, information in the brochure is likely to change without notice.



SIVANANDA ELECTRONICS

DEEPAK MAHAL, LAM ROAD, DEVLALI-422 401, NASHIK. MAHARASHTRA, INDIA.

Phone : 0253-2491423, 2491504, 2491816 E-mail : mkb@sivanandaelectronics.com Fax: 0253-2492291

MUMBAI : 208, MIDAS Sahar Plaza Complex, Andheri Kurla Road, Andheri (E) Mumbai 400059.

Ph: 56430590, Fax : 28389232.

NEW DELHI : G -145, KALKAJI, NEW DELHI -110 019. • PHONE : 6221582, 6434442

BANGALORE : 44/2, DICKENSON ROAD, BANGALORE - 560 042 • PHONE : 5585673

HYDERABAD : 310, JAMUNA MANSION, CHIRAG ALI LANE, ABIDS, HYDERABAD-500 001. • PHONE : 23202943

MFRS. OF : ELECTRONIC INSTRUMENTS, METAL DETECTORS, TURNSTILES, ACCESS CONTROL