



SIVA INSTRUMENTS

Micro Ohm Meter

Model: LS200 A DC



SPECIFICATIONS

Power Supply: 230VAC, $\pm 15\%$, 50Hz ($\pm 5\%$)

Source : 200 A DC Regulated source

Measuring Range: 200A, 100A, 50A & 10A

Resistance Range:
19.999uohm, 199.99 uohm 1999.9uohm & 19.999mohm

Resolution : $.1\mu$ Ohm (at lowest range)

Accuracy : $\pm 1\%$ of reading ± 2 digits

Display : 4 $\frac{1}{2}$ DIGIT, LCD DISPLAY

LED indication for over Temp.

4 Terminal measuring device suitable for Resistance measurement of switch contacts , Bus Bars, Joints, Breaker Contacts, Switchgear, Fuses & low Inductive windings.

SIVANANDA ELECTRONICS also offers C & Tan delta Bridge with High Voltage Power Supply upto 12KV. , SF6 gas filled Standard Capacitors 100 pf/1000 pf upto 20 KV. , Insulation Testers upto 5KV (Solid State),. For detailed information & product catalogue please write to us.

SIVANANDA ELECTRONICS

DEEPAK MAHAL, LAM ROAD, DEVLALI-422 401, NASHIK. MAHARASHTRA, INDIA.

Phone : 0253-2491423, 2491504, 2491816 E-mail : mkb@sivanandaelectronics.com Fax: 0253-2492291

MUMBAI : 208, MIDAS, Sahar Plaza Complex, Andheri Kurla Road, Andheri (E), Mumbai – 400059

PHONE: 022-56430590 / 91 / 92 FAX: 022-28389232.

NEW DELHI : G -145, KALKAJI, NEW DELHI -110 019, PHONE: 6221582, 6434442

MFRS. OF : ELECTRONIC INSTRUMENTS, METAL DETECTORS, TURNSTILES, COMPUTERISED ATTENDANCE RECORDING & ACCESS CONTROL